



# BLUETOOTH BOX S2

**Audiophile aptX Bluetooth audio receiver**

MSRP 149 € (incl. VAT)



**Farboptionen:**



- Wireless music streaming with almost CD-quality
- Bluetooth 3.0
- Supports aptX & SBC codecs
- Easy to install and use
- Fast auto pairing (3 to 5 seconds)
- Up to 8 different Bluetooth sources are memorized
- Works within a range of approximately 10 meters
- RCA stereo analogue and optical Toslink output
- Outboard power supply included
- Antenna included
- Available in silver or black

**Effective working range:** up to 10m (direct visibility)  
**Bluetooth profile:** A2DP  
**Supported codecs:** aptX, SBC  
**Frequency:** 2402 ~ 2480 Mhz  
**Sensitivity:** - 84dBm  
**Maximum received signal at 0.1% BER:** >= -10dBm  
**Maximum level of intermodulation interference:** >= -30dBm  
**Spurious output level:** -156dBm/Hz  
**Audio Output Level (nominal):** 2 Vrms  
**Frequency response:** 20Hz – 20kHz  
**Analogue output:** RCA stereo  
**Digital output:** optical S/PDIF (Toslink)  
**Outboard power supply:** 5V/1000mA DC; 220 - 240V, 50Hz  
**Standby power consumption:** < 1 watt  
**Power consumption:** 200mA DC  
**Dimension W x H x D (D with sockets):** 116 x 37 x 103 (108)mm  
**Weight:** 320 g without power supply

## Bluetooth Box S2: Audiophile wireless streaming with ultimate output flexibility!

Smartphones and tablet computers offer the possibility to stream music wirelessly using Bluetooth protocol. Bluetooth Box S2 is the best solution to use these wireless sources in your own hifi system. Not only standard SBC codecs are supported, but also audiophile aptX with almost CD-quality can be received. Pairing of mobile devices with Bluetooth Box S2 is done fast and playback works reliably within a distance up to 10m with direct visibility. Up to 8 different sources like smartphones and tablets are memorized. Analogue and



digital connection to amplifier or external D/A converter is provided for ultimate flexibility.

