

TAGA[®]
HARMONY

HTA-2500B

Flagship Dual-mono Beast!



HTA-2500B dual-mono 2 x 200W design utilizes 2 high-performance 12AX7-T PSVANE Treasure Mark II vacuum tubes in the preamp section serving as a buffer amplifier and 6 pairs of high-power Sanken transistors (2SC4468/2SA1695) in the output.

Two toroidal transformers with total output of 1200W (600W per channel) provide large amounts of clean power, high voltage stability and very low AC ripple current. This reflects in higher dynamics and extra pure energy and greater abilities to properly drive very demanding and powerful speakers.

Audiophile grade ELNA capacitors ensure stable playback improving music tone and sound field depth.

Audiophile grade Japanese ALPS volume potentiometer provides minimal noises and channels crosstalk and has excellent operational feel and limits errors between the two channels.

Oversized aluminum heat sink system (independent heat sink for each channel) helps to disperse internal heat and allows for long term high power playback with limited distortions.

The high-end class, gold-plated speaker terminals offer almost loss-less audio signal transmission to speakers. Analog inputs with high-end solid machined brass RCA sockets can accommodate up to 2 stereo devices.

You can connect a range of digital devices via optical and coaxial inputs and a built-in high-resolution 24bit / 192kHz DAC (based on Wolfson WM8805 and Cirrus Logic CS4344 circuits) will always provide the best sound performance.

Power Output	2 x 200W, 8ohm 2 x 400W, 4ohm Class A/B
DAC Resolution	24bit / 192kHz
Vacuum Tubes	2 x 12AX7-T PSVANE Treasure Mark II
Wireless connectivity	Bluetooth® v4.0
Inputs	Analog: CD, Line Digital: Optical, Coaxial
Outputs	RCA Pre-Out
Headphones	Impedance: 32-300ohm Output power: 350mW, 300ohm
Signal/Noise ratio	92dB
Frequency Response	20Hz - 35kHz (±0.5dB)
Power Requirements & Consumption	230-240V 50Hz, 1200W (max)
Dimensions (H x W x D)	14 x 43 x 44 cm
Net Weight	21 kg / pc
Finishes	Black